



Satisfy Professional's Needs

**18V+18V Lithium-ion  
DUC302Z Cordless Chain Saw**  
300mm

**LXT**  
LITHIUM-ION



**18V + 18V → 36V**



**Powered by two 18V Li-ion  
batteries in series**



Powered by two 18V Li-ion batteries in series

## Cordless Chain Saw

**DUC302Z** 300mm



The compatible batteries are:



1.5Ah BL1815N



3.0Ah BL1830



4.0Ah BL1840



5.0Ah BL1850

When different capacity batteries are used together (for example, 1.5Ah BL1815N and 3.0Ah BL1830, or fully charged BL1830 and 70% charged BL1830), the machine stops when the battery with less capacity gets empty.

### Increased cutting speed with more powerful motor

# XPT

EXTREME PROTECTION TECHNOLOGY

**Ergonomic top handle and rubberized soft grip**

**Front-hand-guard-activated kickback brake**

- Push of front hand guard stops the blade instantaneously.
- Anti-kickback guard is not needed on the tip of guide bar, increasing blade maneuverability for a wider range of applications.

**Battery capacity warning lamp**

**DUC302Z:**  
with sprocket nose guide bar.



**New adjustment system for easier tool-less saw chain tension adjustment**

Extendable lever provides tightening torque.

Dial for easier adjustment of saw chain tension



**Retractable metal hook**  
allows to check how much oil is left from outside.

**Chain oil level window**  
allows to check how much oil is left from outside.



**Adjusting the chain lubrication**

You can adjust the oil pump feed rate with the adjusting screw.

### Cordless Chain Saw

**DUC302Z** 300mm

442

Chain speed per minute	500m
Guide bar length	300mm
Chain blade	Pitch : 3/8"
Sound pressure level	84.4dB(A)
Sound power level	95.4dB(A)
Dimensions (L x W x H)	600x234x198mm
Net weight* With two BL1815N batteries:	4.1kg
With two BL1830 or BL1840 batteries:	4.7kg



Brake



Chain Brake



Automatic Oiling

**Standard Equipment :**

Saw Chain, Guide Bar, Guide Bar Cover

\*weight according to EPTA-Procedure 01/2003

Items of standard equipment and specifications may vary by country or area.

# Batteries and Charger Not Included