



Satisfy Professional's Needs

Random Orbit Sander BO5031



Ergonomically Contoured Grip with Non-Skid Elastomer Covered Surface

Fits Your Palm

perfectly



Smooth and Clean Sanding



Speed control dial
4,000-12,000opm

Dust Bag or Dust box with Paper filter
Both dust collection systems are ready.

Dust box
assembly
Part No. 135246-0

Paper filter
5pcs/ set
Part No. 194746-9

Dust can be thrown away with Paper filter.

Rubber switch cover
prevents ingress of dust.

Bearing section
with increased
durability

obtained by using larger
size ball bearing

Pad brake
quickly stops motor after
power switch is turned off.

Connectable to Makita vacuum
cleaners without adapter



High power motor and
orbit action for heavy
duty applications



High dust
extraction
rate



Powerful
**300
W**

Accessories

Hose 28-1.5
Part No. 192278-0



Wool Pad
Part No. 794560-9



Sponge Pad
Part No. 794558-6



Felt Pad
Part No. 794559-4



Random Orbit Sander



Double Insulation



Dust Collecting



Hook & Loop



Variable Speed



BO5031

BO5031

419

Continuous rating Input 300W
Pad diameter 123mm
Abrasive disc diameter 125mm
Orbits per minute (o/min) 4,000-12,000

Dimensions (L x W x H) 153 x 123 x 153mm
Net weight 1.3kg
Power supply cord 2.0m

Standard Equipment

Abrasive Disc, Dust Bag or Dust Box